



SupraLink DX Receiver V 5.8GHz

Indoor receiver for video and audio signals

Frequency range: 5.725 - 5.875GHz

Channels: 16 (Selector switch)

Video output: $1V_{ss} \pm 0.1V_{ss}$ @ 75Ohm

Video bandwidth: 30Hz - 5MHz

Audio output: 500mVeff an <1kOhm

Audio bandwidth: 15Hz - 16kHz (3dB)

Power supply: 7 - 30V DC

Dimensions: 117 x 68 x 35mm (w/o antenna)

Weight: 230g

Features:

- » connector for external antenna
- » Audio stereo
- » Channel display
- » Switching channel
- » Displaying of the relative field strength of the reception field
- » Video inverse function
- » Automatic channel switching
- » Video-Audio mute function
- » 5V output for antenna pre-amplifier
- » Video-Detect output
- » Antenna Diversity (optional)
- » Channel-scan function (optional)

Connectors:

- » Video (BNC)
- » Audio (jack)
- » Switch (terminal)
- » Antenna (SMA)
- » DC (1.35 / 5.5mm)